

Technical Specifications

Power supply	1x 3V CR2032
Power consumption	typ. 3.3 μ W, max. 51mW
Power loss	max. 51mW
Battery lifetime	up to 2 years
Interfaces	Loxone Air: 868MHz (SRD Band Europe), 4 channels available max. Power 15.1mW e.r.p. 915MHz (ISM Band Region 2), 10 channels available max. Power 13.2mW
Ambient temperature	-20 ... 60°C / 0 ... 140°F
Humidity	max. 95% r. H. (non condensing)
Touch points	1 Touch point, tactile switch
Feedback	visual
Safety rating	IP64
Dimensions	84x84x30.5mm / 3.31x3.31x1.2" (LxWxH)
Maintenance & Cleaning	This device is free of maintenance and may only be cleaned with a dry cloth.

LOXONE

Need Help?

loxone.com/support

Loxone Electronics GmbH
Smart Home 1
4154 Kollerschlag
Austria

loxone.com



L2504.A

LOXONE



Wrist Button Air

Part No: 100496

About the product

The Wrist Button Air is an individually configurable, battery-powered button that can be worn comfortably on the wrist. An action triggered by the Wrist Button Air is indicated by a flashing red LED.

Features

- Large single pushbutton
- Visual feedback

Installation

The Wrist Button Air is powered by a CR2032 battery. Once the Wrist Button Air is assembled simply configure it in Loxone Config in the usual way.

The installation of this device has to be carried out by a qualified person. The device has to be fitted in accordance with building regulations for electrical and fire safety. If the device is not installed according to manufacturers guidelines the protection of the device may be affected.

Information

Contains FCC ID: ARR-V-000375

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference
2. This device must accept any interference received, including interference that may cause undesired operation



For additional information, declaration of conformity, visit www.loxone.com/help/wrist-button-air